





## Sensors and potentiometers supply input 24Vdc / output 10Vdc 0.6A

<b>Series</b>	
<b>Code</b>	X766184
<b>Type</b>	CWCV7-6184 -
<b>HS code</b>	85049090
<b>INPUT TECHNICAL DATA</b>	
<b>Input rated voltage</b>	24 Vdc (16.8...30 Vdc)
<b>Current consumption</b>	30 mA at 10 Vdc
<b>Internal protection fuse</b>	T 1 A (external)
<b>OUTPUT TECHNICAL DATA</b>	
<b>Output rated voltage</b>	10 Vdc (9...11 Vdc adjustable)
<b>Continuous current</b>	60 mA
<b>Overload limiting</b>	yes
<b>Ripple</b>	
<b>Status indication</b>	LED "DC OK"
<b>GENERAL TECHNICAL DATA</b>	
<b>Operating temperature range</b>	-25...+60°C
<b>Insulation</b>	50 Vac / 60 s
<b>Insulation type</b>	2-way
<b>Standard approvals</b>	EN 50081-1, EN 50082-2, EN 61000-3-2
<b>EMC Standard</b>	EN61000-4-2, EN61000-4-4
<b>Overvoltage category / pollution degree</b>	II / 2
<b>Protection degree</b>	IP 20
<b>Connection terminal IN / OUT</b>	1.5 mm <sup>2</sup> / 1.5 mm <sup>2</sup> (screw)
<b>Housing material</b>	UL94V-0 plastic material
<b>Dimensions (LxHxD)</b>	6.2x92.5x90 mm
<b>Approximate weight</b>	35 g
<b>Mounting information</b>	on a rail, side by side
<b>ACCESSORIES</b>	
<b>Mounting rail (IEC60715/TH35-7.5)</b>	PR/3/AC, PR/3/AC/ZB, PR/3/AS, PR/3/AS/ZB
<b>Plugin jumper red</b>	CWBK 7-0802 (code X766802)
<b>Plugin jumper white</b>	CWBK 7-0804 (code X766804)
<b>Plugin jumper blue</b>	CWBK 7-0804 (code X766804)
<b>APPROVALS AND MARKINGS</b>	CE



\* Regulated switching converter\* Suitable for feeding potentiometers and sensors

## DESCRIZIONE DEL PRODOTTO

CWCV7-6184 Sensors and potentiometers supply input 24Vdc / output 10Vdc 0.6A